



Dimmer Compatibility Chart on OVEDRRIVE Dimmable LED lamps

| No. | Dimmer Maker | IMAGE | Dimmer Type |  |  |
|------|----------------|---------------------------|------------------------------|---|---|
| | | Overdrive Item # | | 601 | 585 |
| | | Overdrive Model # | | L10HDL4DI M/27K | L12HDL6DIM/ 30K |
| 1-1 | LEVITON | R62-6683-IW | forward phase(leading edge) | √ | √ |
| 1-2 | | C20-6681-IW | forward phase(leading edge) | x | x |
| 1-3 | | R01-RPI06-1LI | forward phase(leading edge) | x | x |
| 1-4 | | 6674-10W | forward phase(leading edge) | √ | √ |
| 1-5 | | R02-6615-POW | reverse phase(trailing edge) | √ | √ |
| 1-6 | | R15-IPI06-1SE | forward phase(leading edge) | √ | √ |
| 1-7 | | 1PE04-1LZ | reverse phase(trailing edge) | √ | √ |
| 1-8 | | R50-6602-IW | forward phase(leading edge) | √ | √ |
| 1-9 | | 6633 | forward phase(leading edge) | √ | √ |
| 1-10 | | IPL06 | forward phase(leading edge) | √ | √ |
| 2-1 | LUTRON | TTCL-100H-WH | forward phase(leading edge) | √ | √ |
| 2-2 | | D-600PH-DK | forward phase(leading edge) | x | x |
| 2-3 | | DVLV-600P-WH | forward phase(leading edge) | √ | √ |
| 2-4 | | NTLV-600-WH | forward phase(leading edge) | √ | √ |
| 2-5 | | DVELV-300P-WH | reverse phase(trailing edge) | √ | √ |
| 2-6 | | DV-603PG-WH | forward phase(leading edge) | √ | √ |
| 2-7 | | NLV-600-WH | forward phase(leading edge) | √ | √ |
| 2-8 | | CTCL-153PDH | forward phase(leading edge) | √ | √ |
| 2-9 | | D-603PH | forward phase(leading edge) | x | x |
| 2-10 | | TT-300NLN-WH | forward phase(leading edge) | √ | x |
| 2-11 | | MRF2-3PD-1-1WH(Digital) | forward phase(leading edge) | √ | √ |
| 2-12 | | MA-600-WH(Digital) | forward phase(leading edge) | √ | √ |
| 2-13 | | MAW-600(Digital) | forward phase(leading edge) | √ | √ |
| 2-14 | | MRF2-6ND-120-WH(Digital) | forward phase(leading edge) | √ | √ |
| 2-15 | | RRD-10ND-WH(Digital) | forward phase(leading edge) | √ | √ |
| 2-16 | | VTELV-600M-B-WH(Digital) | forward phase(leading edge) | √ | √ |
| 2-17 | | MAELV-600-WH(Digital) | reverse phase(trailing edge) | √ | √ |
| 2-18 | | MRF2-6ELV-120-WH(Digital) | reverse phase(trailing edge) | √ | √ |
| 2-19 | | AYCL-153P-WH | reverse phase(trailing edge) | √ | √ |
| 2-20 | | AYLV-600P-WH | forward phase(leading edge) | √ | √ |
| 2-21 | | TG-603PGH-WH | forward phase(leading edge) | √ | √ |
| 2-22 | | S-600PR-WH | forward phase(leading edge) | √ | √ |
| 2-23 | | CTCL-153P-WH | forward phase(leading edge) | √ | √ |
| 2-24 | | MACL-153M-WH (Digital) | forward phase(leading edge) | √ | √ |
| 2-25 | | DVCL-153P-WH | forward phase(leading edge) | √ | √ |
| 2-26 | | SCL-153PH-WH-C | forward phase(leading edge) | √ | √ |
| 2-27 | | LGCL-153PLH-WH-C | forward phase(leading edge) | √ | √ |
| 2-28 | | TGCL-153PH-WH-C | forward phase(leading edge) | √ | √ |
| 3-1 | LEGRAND | DRD4-B(Digital) | forward phase(leading edge) | √ | √ |
| 4-1 | PASS & SEYMOUR | CD703-PW | forward phase(leading edge) | √ | √ |
| 4-2 | | CDLV703-P | forward phase(leading edge) | √ | √ |
| 4-3 | | D703-PTC | forward phase(leading edge) | √ | √ |
| 4-4 | | DLV703-P | forward phase(leading edge) | √ | √ |